

# SPECIFICATIONS

## Standard

### Math Tools

Display up to four math function traces (F1-F4). The easy-to-use graphical interface simplifies setup of up to two operations on each function trace; and function traces can be chained together to perform math-on-math.

absolute value	integral
average (summed)	invert (negate)
average (continuous)	log (base e)
custom (MATLAB) – limited points	product (x)
derivative	ratio (/)
deskew (resample)	reciprocal
difference (-)	rescale (with units)
enhanced resolution (to 11 bits vertical)	roof
envelope	(sinx)/x
exp (base e)	square
exp (base 10)	square root
fft (power spectrum, magnitude, phase, up to 50 kpts)	sum (+)
floor	trend (datalog) of 1000 events
histogram of 1000 events	zoom (identity)

### Measure Tools

Display any 6 parameters together with statistics, including their average, high, low, and standard deviations. Histicons provide a fast, dynamic view of parameters and wave-shape characteristics.

amplitude	frequency	risetime (10–90%, 20–80%, @ level)
area	last	rms
base	level @ x	std. deviation
cycles	maximum	time @ level
custom (MATLAB, VBScript) – limited points	mean	top
delay	median	$\Delta$ time @ level
$\Delta$ delay	minimum	$\Delta$ time @ level from trigger
duration	number of points	width (positive + negative)
duty cycle	+overshoot	x@ max.
falltime (90–10%, 80–20%, @ level)	-overshoot	x@ min.
first	peak-to-peak	
	period	
	phase	

### Pass/Fail Testing

Simultaneously test multiple parameters against selectable parameter limits or pre-defined masks. Pass or fail conditions can initiate actions including document to local or networked files, e-mail the image of the failure, save waveforms, send a pulse out at the rear panel auxiliary BNC output, or (with the GPIB option) send a GPIB SRQ.

### Jitter and Timing Analysis Software Package (WRXi-JTA2) (Standard with MXi-A model oscilloscopes)

- Jitter and timing parameters, with "Track" graphs of
  - Cycle-Cycle Jitter
  - N-Cycle
  - N-Cycle with start selection
  - Frequency
- Edge@lv parameter (counts edges)
- Persistence histogram, persistence trace (mean, range, sigma)

## Software Options – Advanced Math and WaveShape Analysis

### Statistics Package (WRXi-STAT)

This package provides additional capability to statistically display measurement information and to analyze results:

- Histograms expanded with 19 histogram parameters/up to 2 billion events.
- Persistence Histogram
- Persistence Trace (mean, range, sigma)

### Master Analysis Software Package (WRXi-XMAP) (Standard with MXi-A model oscilloscopes)

This package provides maximum capability and flexibility, and includes all the functionality present in XMATH, XDEV, and JTA2.

### Advanced Math Software Package (WRXi-XMATH) (Standard with MXi-A model oscilloscopes)

This package provides a comprehensive set of WaveShape Analysis tools providing insight into the wave shape of complex signals. Includes:

- Parameter math – add, subtract, multiply, or divide two different parameters. Invert a parameter and rescale parameter values.
- Histograms expanded with 19 histogram parameters/up to 2 billion events.
- Trend (datalog) of up to 1 million events
- Track graphs of any measurement parameter
- FFT capability includes: power averaging, power density, real and imaginary components, frequency domain parameters, and FFT on up to 24 Mpts.
- Narrow-band power measurements
- Auto-correlation function
- Sparse function
- Cubic interpolation function

### Advanced Customization Software Package (WRXi-XDEV) (Standard with MXi-A model oscilloscopes)

This package provides a set of tools to modify the scope and customize it to meet your unique needs. Additional capability provided by XDEV includes:

- Creation of your own measurement parameter or math function, using third-party software packages, and display of the result in the scope. Supported third-party software packages include:
  - VBScript – MATLAB – Excel
- CustomDSO – create your own user interface in a scope dialog box.
- Addition of macro keys to run VBScript files
- Support for plug-ins

### Value Analysis Software Package (WRXi-XVAP) (Standard with MXi-A model oscilloscopes)

#### Measurements:

- Jitter and Timing parameters (period@level, width@level, edge@level, duty@level, time interval error@level, frequency@level, half period, setup, skew,  $\Delta$  period@level,  $\Delta$  width@level).

#### Math:

- Persistence histogram
- Persistence trace (mean, sigma, range)
- 1 Mpts FFTs with power spectrum density, power averaging, real, imaginary, and real+imaginary settings)

#### Statistical and Graphical Analysis

- 1 Mpts Trends and Histograms
- 19 histogram parameters
- Track graphs of any measurement parameter

### Intermediate Math Software Package (WRXi-XWAV)

#### Math:

- 1 Mpts FFTs with power spectrum density, power averaging, real, and imaginary components

#### Statistical and Graphical Analysis

- 1 Mpts Trends and Histograms
- 19 histogram parameters
- Track graphs of any measurement parameter

# SPECIFICATIONS

	WaveRunner 44Xi-A 44MXi-A	WaveRunner 64Xi-A 64MXi-A	WaveRunner 62Xi-A	WaveRunner 104Xi-A 104MXi-A	WaveRunner 204Xi-A 204MXi-A
<b>Vertical System</b>					
Nominal Analog Bandwidth @ 50 Ω, 10 mV–1 V/div	400 MHz	600 MHz	600 MHz	1 GHz	2 GHz
Rise Time (Typical)	875 ps	500 ps	500 ps	300 ps	180 ps
Input Channels	4	4	2	4	4
Bandwidth Limiters	20 MHz; 200 MHz				
Input Impedance	1 MΩ    16 pF or 50 Ω			1 MΩ    20 pF or 50 Ω	
Input Coupling	50 Ω: DC, 1 MΩ: AC, DC, GND				
Maximum Input Voltage	50 Ω: 5 V <sub>rms</sub> ; 1 MΩ: 400 V max. (DC + Peak AC ≤ 5 kHz)			50 Ω: 5 V <sub>rms</sub> , 1 MΩ: 250 V max. (DC + Peak AC ≤ 10 kHz)	
Vertical Resolution	8 bits; up to 11 with enhanced resolution (ERES)				
Sensitivity	50 Ω: 2 mV/div–1 V/div fully variable; 1 MΩ: 2 mV–10 V/div fully variable				
DC Gain Accuracy	±1.0% of full scale (typical); ±1.5% of full scale, ≥ 10 mV/div (warranted)				
Offset Range	50 Ω: ±1 V @ 2–98 mV/div, ±10 V @ 100 mV/div–1 V/div; 1 MΩ: ±1 V @ 2–98 mV/div, ±10 V @ 100 mV/div–1 V/div, ±100 V @ 1.02 V/div–10 V/div			50 Ω: ±400 mV @ 2–4.95 mV/div, ±1 V @ 5–99 mV/div, ±10 V @ 100 mV–1 V/div 1 MΩ: ±400 mV @ 2–4.95 mV/div, ±1 V @ 5–99 mV/div, ±10 V @ 100 mV–1 V/div, ±100 V @ 1.02–10 V/div	
Input Connector	ProBus/BNC				
<b>Timebase System</b>					
Timebases	Internal timebase common to all input channels; an external clock may be applied at the auxiliary input				
Time/Division Range	Real time: 200 ps/div–10 s/div, RIS mode: 200 ps/div to 10 ns/div, Roll mode: up to 1,000 s/div				
Clock Accuracy	≤ 5 ppm @ 25 °C (typical) (≤ 10 ppm @ 5–40 °C)				
Sample Rate and Delay Time Accuracy	Equal to Clock Accuracy				
Channel to Channel Deskew Range	±9 x time/div setting, 100 ms max., each channel				
External Sample Clock	DC to 600 MHz; (DC to 1 GHz for 104Xi-A/104MXi-A and 204Xi-A/204MXi-A) 50 Ω, (limited BW in 1 MΩ), BNC input, limited to 2 Ch operation (1 Ch in 62Xi-A), (minimum rise time and amplitude requirements apply at low frequencies)				
Roll Mode	User selectable at ≥ 500 ms/div and ≤ 100 KS/s				
<b>Acquisition System</b>	<b>44Xi-A 44MXi-A</b>	<b>64Xi-A 64MXi-A</b>	<b>62Xi-A</b>	<b>104Xi-A 104MXi-A</b>	<b>204Xi-A 204MXi-A</b>
Single-Shot Sample Rate/Ch	5 GS/s				
Interleaved Sample Rate (2 Ch)	5 GS/s	10 GS/s	10 GS/s	10 GS/s	10 GS/s
Random Interleaved Sampling (RIS)	200 GS/s				
RIS Mode	User selectable from 200 ps/div to 10 ns/div			User selectable from 100 ps/div to 10 ns/div	
Trigger Rate (Maximum)	1,250,000 waveforms/second				
Sequence Time Stamp Resolution	1 ns				
Minimum Time Between Sequential Segments	800 ns				
Acquisition Memory Options	Max. Acquisition Points (4 Ch/2 Ch, 2 Ch/1 Ch in 62Xi-A) Standard 12.5M/25M			Segments (Sequence Mode) 10,000	
<b>Acquisition Processing</b>	<b>44Xi-A 44MXi-A</b>	<b>64Xi-A 64MXi-A</b>	<b>62Xi-A</b>	<b>104Xi-A 104MXi-A</b>	<b>204Xi-A 204MXi-A</b>
Time Resolution (min, Single-shot)	200 ps (5 GS/s)	100 ps (10 GS/s)	100 ps (10 GS/s)	100 ps (10 GS/s)	100 ps (10 GS/s)
Averaging	Summed and continuous averaging to 1 million sweeps				
ERES	From 8.5 to 11 bits vertical resolution				
Envelope (Extrema)	Envelope, floor, or roof for up to 1 million sweeps				
Interpolation	Linear or (Sinx)/x				
<b>Trigger System</b>					
Trigger Modes	Normal, Auto, Single, Stop				
Sources	Any input channel, External, Ext/10, or Line; slope and level unique to each source, except Line				
Trigger Coupling	DC, AC (typically 7.5 Hz), HF Reject, LF Reject				
Pre-trigger Delay	0–100% of memory size (adjustable in 1% increments, or 100 ns)				
Post-trigger Delay	Up to 10,000 divisions in real time mode, limited at slower time/div settings in roll mode				
Hold-off	1 ns to 20 s or 1 to 1,000,000,000 events				

# SPECIFICATIONS

	WaveRunner 44Xi-A 44MXi-A	WaveRunner 64Xi-A 64MXi-A	WaveRunner 62Xi-A	WaveRunner 104Xi-A 104MXi-A	WaveRunner 204Xi-A 204MXi-A
<b>Trigger System (cont'd)</b>					
Internal Trigger Level Range	±4.1 div from center (typical)				
Trigger and Interpolator Jitter	≤ 3 ps rms (typical)				
Trigger Sensitivity with Edge Trigger (Ch 1–4 + external, DC, AC, and LFreq coupling)	2 div @ < 400 MHz 1 div @ < 200 MHz	2 div @ < 600 MHz 1 div @ < 200 MHz	2 div @ < 600 MHz 1 div @ < 200 MHz	2 div @ < 1 GHz 1 div @ < 200 MHz	2 div @ < 2 GHz 1 div @ < 200 MHz
Max. Trigger Frequency with SMART Trigger™ (Ch 1–4 + external)	400 MHz @ ≥ 10 mV	600 MHz @ ≥ 10 mV	600 MHz @ ≥ 10 mV	1 GHz @ ≥ 10 mV	2 GHz @ ≥ 10 mV
External Trigger Range	EXT/10 ±4 V; EXT ±400 mV				
<b>Basic Triggers</b>					
Edge	Triggers when signal meets slope (positive, negative, either, or Window) and level condition				
TV-Composite Video	Triggers NTSC or PAL with selectable line and field; HDTV (720p, 1080i, 1080p) with selectable frame rate (50 or 60 Hz) and Line; or CUSTOM with selectable Fields (1–8), Lines (up to 2000), Frame Rates (25, 30, 50, or 60 Hz), Interlacing (1:1, 2:1, 4:1, 8:1), or Synch Pulse Slope (Positive or Negative)				
<b>SMART Triggers</b>					
State or Edge Qualified	Triggers on any input source only if a defined state or edge occurred on another input source. Delay between sources is selectable by time or events				
Qualified First	In Sequence acquisition mode, triggers repeatedly on event B only if a defined pattern, state, or edge (event A) is satisfied in the first segment of the acquisition. Delay between sources is selectable by time or events				
Dropout	Triggers if signal drops out for longer than selected time between 1 ns and 20 s.				
Pattern	Logic combination (AND, NAND, OR, NOR) of 5 inputs (4 channels and external trigger input – 2 Ch+EXT on WaveRunner 62Xi-A). Each source can be high, low, or don't care. The High and Low level can be selected independently. Triggers at start or end of the pattern				
<b>SMART Triggers with Exclusion Technology</b>					
Glitch and Pulse Width	Triggers on positive or negative glitches with widths selectable from 500 ps to 20 s or on intermittent faults (subject to bandwidth limit of oscilloscope)				
Signal or Pattern Interval	Triggers on intervals selectable between 1 ns and 20 s				
Timeout (State/Edge Qualified)	Triggers on any source if a given state (or transition edge) has occurred on another source. Delay between sources is 1 ns to 20 s, or 1 to 99,999,999 events				
Runt	Trigger on positive or negative runts defined by two voltage limits and two time limits. Select between 1 ns and 20 s				
Slew Rate	Trigger on edge rates. Select limits for dV, dt, and slope. Select edge limits between 1 ns and 20 s				
Exclusion Triggering	Trigger on intermittent faults by specifying the normal width or period				
<b>LeCroy WaveStream Fast Viewing Mode</b>					
Intensity	256 Intensity Levels, 1–100% adjustable via front panel control				
Number of Channels	up to 4 simultaneously				
Max Sampling Rate	5 GS/s (10 GS/s for WR 62Xi-A, 64Xi-A/64MXi-A, 104Xi-A/104MXi-A, 204Xi-A/204MXi-A in interleaved mode)				
Waveforms/second (continuous)	Up to 20,000 waveforms/second				
Operation	Front panel toggle between normal real-time mode and LeCroy WaveStream Fast Viewing mode				
<b>Automatic Setup</b>					
Auto Setup	Automatically sets timebase, trigger, and sensitivity to display a wide range of repetitive signals				
Vertical Find Scale	Automatically sets the vertical sensitivity and offset for the selected channels to display a waveform with maximum dynamic range				
<b>Probes</b>	<b>44Xi-A 44MXi-A</b>	<b>64Xi-A 64MXi-A</b>	<b>62Xi-A</b>	<b>104Xi-A 104MXi-A</b>	<b>204Xi-A 204MXi-A</b>
Probes	One Passive probe per channel; Optional passive and active probes available				
Probe System; ProBus	Automatically detects and supports a variety of compatible probes				
Scale Factors	Automatically or manually selected, depending on probe used				
<b>Color Waveform Display</b>					
Type	Color 10.4" flat-panel TFT-LCD with high resolution touch screen				
Resolution	SVGA; 800 x 600 pixels; maximum external monitor output resolution of 2048 x 1536 pixels				
Number of Traces	Display a maximum of 8 traces. Simultaneously display channel, zoom, memory, and math traces				
Grid Styles	Auto, Single, Dual, Quad, Octal, XY, Single + XY, Dual + XY				
Waveform Styles	Sample dots joined or dots only in real-time mode				

# SPECIFICATIONS

## Zoom Expansion Traces

Display up to 4 Zoom/Math traces with 16 bits/data point

## Internal Waveform Memory

M1, M2, M3, M4 Internal Waveform Memory (store full-length waveform with 16 bits/data point) or store to any number of files limited only by data storage media

## Setup Storage

Front Panel and Instrument Status Store to the internal hard drive, over the network, or to a USB-connected peripheral device

## Interface

Remote Control	Via Windows Automation, or via LeCroy Remote Command Set
Network Communication Standard	VXI-11 or VICP, LXI Class C Compliant
GPIB Port (Accessory)	Supports IEEE – 488.2
Ethernet Port	10/100/1000Base-T Ethernet interface (RJ-45 connector)
USB Ports	5 USB 2.0 ports (one on front of instrument) supports Windows-compatible devices
External Monitor Port	Standard 15-pin D-Type SVGA-compatible DB-15; connect a second monitor to use extended desktop display mode with XGA resolution
Serial Port	DB-9 RS-232 port (not for remote oscilloscope control)

**44Xi-A      64Xi-A      62Xi-A      104Xi-A      204Xi-A**  
**44MXi-A      64MXi-A      104MXi-A      204MXi-A**

Signal Types	Selected from External Trigger or External Clock input on front panel
Coupling	50 Ω: DC, 1 MΩ: AC, DC, GND
Maximum Input Voltage	50 Ω: 5 V <sub>rms</sub> , 1 MΩ: 400 V max. (DC + Peak AC ≤ 5 kHz)
	50 Ω: 5 V <sub>rms</sub> , 1 MΩ: 250 V max. (DC + Peak AC ≤ 10 kHz)

## Auxiliary Output

Signal Type	Trigger Enabled, Trigger Output, Pass/Fail, or Off
Output Level	TTL, ≈3.3 V
Connector Type	BNC, located on rear panel

## General

Auto Calibration	Ensures specified DC and timing accuracy is maintained for 1 year minimum
Calibrator	Output available on front panel connector provides a variety of signals for probe calibration and compensation
Power Requirements	90–264 V <sub>rms</sub> at 50/60 Hz; 115 V <sub>rms</sub> (±10%) at 400 Hz, Automatic AC Voltage Selection Installation Category: 300 V CAT II; Max. Power Consumption: 340 VA/340 W; 290 VA/290 W for WaveRunner 62Xi-A

## Environmental

Temperature: Operating	+5 °C to +40 °C
Temperature: Non-Operating	-20 °C to +60 °C
Humidity: Operating	Maximum relative humidity 80% for temperatures up to 31 °C decreasing linearly to 50% relative humidity at 40 °C
Humidity: Non-Operating	5% to 95% RH (non-condensing) as tested per MIL-PRF-28800F
Altitude: Operating	Up to 3,048 m (10,000 ft.) @ ≤ 25 °C
Altitude: Non-Operating	Up to 12,190 m (40,000 ft.)

## Physical

Dimensions (HWD)	260 mm x 340 mm x 152 mm Excluding accessories and projections (10.25" x 13.4" x 6")
Net Weight	7.26 kg. (16.0 lbs.)

## Certifications

CE Compliant, UL and cUL listed; Conforms to EN 61326, EN 61010-1, UL 61010-1 2nd Edition, and CSA C22.2 No. 61010-1-04

## Warranty and Service

3-year warranty; calibration recommended annually. Optional service programs include extended warranty, upgrades, calibration, and customization services

# ORDERING INFORMATION

## OPTIONAL EQUIPMENT

Product Description	Product Code	Product Description	Product Code
<b>WaveRunner Xi-A Series Oscilloscopes</b>			
2 GHz, 4 Ch, 5 GS/s, 12.5 Mpts/Ch (10 GS/s, 25 Mpts/Ch in interleaved mode) with 10.4" Color Touch Screen Display	WaveRunner 204Xi-A	Jitter and Timing Analysis Software Package (Standard with MXi-A model oscilloscopes)	WRXi-JTA2
1 GHz, 4 Ch, 5 GS/s, 12.5 Mpts/Ch (10 GS/s, 25 Mpts/Ch in interleaved mode) with 10.4" Color Touch Screen Display	WaveRunner 104Xi-A	Digital Filter Software Package	WRXi-DFP2
600 MHz, 4 Ch, 5 GS/s, 12.5 Mpts/Ch (10 GS/s, 25 Mpts/Ch in interleaved mode) with 10.4" Color Touch Screen Display	WaveRunner 64Xi-A	Disk Drive Measurement Software Package	WRXi-DDM2
600 MHz, 2 Ch, 5 GS/s, 12.5 Mpts/Ch (10 GS/s, 25 Mpts/Ch in interleaved mode) with 10.4" Color Touch Screen Display	WaveRunner 62Xi-A	PowerMeasure Analysis Software Package	WRXi-PMA2
400 MHz, 4 Ch, 5 GS/s, 12.5 Mpts/Ch (25 Mpts/Ch in interleaved mode) with 10.4" Color Touch Screen Display	WaveRunner 44Xi-A	Serial Data Mask Software Package	WRXi-SDM
<b>WaveRunner MXi-A Series Oscilloscopes</b>			
2 GHz, 4 Ch, 5 GS/s, 12.5 Mpts/Ch (10 GS/s, 25 Mpts/Ch in Interleaved Mode) with 10.4" Color Touch Screen Display	WaveRunner 204MXi-A	QualiPHY Enabled Ethernet Software Option	QPHY-ENET*
1 GHz, 4 Ch, 5 GS/s, 12.5 Mpts/Ch (10 GS/s, 25 Mpts/Ch in Interleaved Mode) with 10.4" Color Touch Screen Display	WaveRunner 104MXi-A	QualiPHY Enabled USB 2.0 Software Option	QPHY-USB†
600 MHz, 4 Ch, 5 GS/s, 12.5 Mpts/Ch (10 GS/s, 25 Mpts/Ch in Interleaved Mode) with 10.4" Color Touch Screen Display	WaveRunner 64MXi-A	EMC Pulse Parameter Software Package	WRXi-EMC
400 MHz, 4 Ch, 5 GS/s, 12.5 Mpts/Ch (25 Mpts/Ch in Interleaved Mode) with 10.4" Color Touch Screen Display	WaveRunner 44MXi-A	Electrical Telecom Mask Test Package	ET-PMT
<b>Included with Standard Configuration</b>			
±10, 500 MHz, 10 MΩ Passive Probe (Total of 1 Per Channel)		* TF-ENET-B required. † TF-USB-B required.	
Standard Ports; 10/100/1000Base-T Ethernet, USB 2.0 (5), SVGA Video out, Audio in/out, RS-232			
Optical 3-button Wheel Mouse – USB 2.0			
Protective Front Cover			
Accessory Pouch			
Getting Started Manual			
Quick Reference Guide			
Anti-virus Software (Trial Version)			
Commercial NIST Traceable Calibration with Certificate			
3-year Warranty		A variety of Vehicle Bus Analyzers based on the WaveRunner Xi-A platform are available. These units are equipped with a Symbolic CAN trigger and decode.	
<b>General Purpose Software Options</b>			
Statistics Software Package	WRXi-STAT	<b>Mixed Signal Oscilloscope Options</b>	
Master Analysis Software Package (Standard with MXi-A model oscilloscopes)	WRXi-XMAP	500 MHz, 18 Ch, 2 GS/s, 50 Mpts/Ch Mixed Signal Oscilloscope Option	MS-500
Advanced Math Software Package (Standard with MXi-A model oscilloscopes)	WRXi-XMATH	250 MHz, 36 Ch, 1 GS/s, 25 Mpts/Ch (500 MHz, 18 Ch, 2 GS/s, 50 Mpts/Ch Interleaved) Mixed Signal Oscilloscope Option	MS-500-36
Intermediate Math Software Package (Standard with MXi-A model oscilloscopes)	WRXi-XWAV	250 MHz, 18 Ch, 1 GS/s, 10 Mpts/Ch Mixed Signal Oscilloscope Option	MS-250
Value Analysis Software Package (Includes XWAV and JTA2) (Standard with MXi-A model oscilloscopes)	WRXi-XVAP	<b>Probes and Amplifiers*</b>	
Advanced Customization Software Package (Standard with MXi-A model oscilloscopes)	WRXi-XDEV	Set of 4 ZS1500, 1.5 GHz, 0.9 pF, 1 MΩ High Impedance Active Probe	ZS1500-QUADPAK
Spectrum Analyzer and Advanced FFT Option	WRXi-SPECTRUM	Set of 4 ZS1000, 1 GHz, 0.9 pF, 1 MΩ <sup>†</sup> High Impedance Active Probe	ZS1000-QUADPAK
Processing Web Editor Software Package	WRXi-XWEB	2.5 GHz, 0.7 pF Active Probe	HFP2500
		1 GHz Active Differential Probe (-1, +10, -20)	AP034
		500 MHz Active Differential Probe (x10, -1, +10, -100)	AP033
		30 A; 100 MHz Current Probe – AC/DC; 30 A <sub>rms</sub> ; 50 A <sub>rms</sub> Pulse	CP031
		30 A; 50 MHz Current Probe – AC/DC; 30 A <sub>rms</sub> ; 50 A <sub>rms</sub> Pulse	CP030
		30 A; 50 MHz Current Probe – AC/DC; 30 A <sub>rms</sub> ; 50 A <sub>peak</sub> Pulse	AP015
		150 A; 10 MHz Current Probe – AC/DC; 150 A <sub>rms</sub> ; 500 A <sub>peak</sub> Pulse	CP150
		500 A; 2 MHz Current Probe – AC/DC; 500 A <sub>rms</sub> ; 700 Apeak Pulse	CP500
		1,400 V, 100 MHz High-Voltage Differential Probe	ADP305
		1,400 V, 20 MHz High-Voltage Differential Probe	ADP300
		1 Ch, 100 MHz Differential Amplifier	DA1855A

\*A wide variety of other passive, active, and differential probes are also available.  
Consult LeCroy for more information.

# ORDERING INFORMATION

## OPTIONAL ACCESSORIES

Product Description	Product Code
<b>Hardware Accessories*</b>	
10/100/1000Base-T Compliance Test Fixture	TF-ENET-B <sup>†</sup>
USB 2.0 Compliance Test Fixture	TF-USB-B
External GPIB Interface	WS-GPIB
Soft Carrying Case	WRXi-SOFTCASE
Hard Transit Case	WRXi-HARDCASE
Mounting Stand – Desktop Clamp Style	WRXi-MS-CLAMP
Rackmount Kit	WRXi-RACK
Mini Keyboard	WRXi-KYBD
Removable Hard Drive Package (Includes removable hard drive kit and two hard drives)	WRXi-A-RHD
Additional Removable Hard Drive	WRXi-A-RHD-02

\* A variety of local language front panel overlays are also available.

† Includes ENET-2CAB-SMA018 and ENET-2ADA-BNCSMA.

## Customer Service

LeCroy oscilloscopes and probes are designed, built, and tested to ensure high reliability. In the unlikely event you experience difficulties, our digital oscilloscopes are fully warranted for three years, and our probes are warranted for one year.

This warranty includes:

- No charge for return shipping
- Long-term 7-year support
- Upgrade to latest software at no charge



1-800-5-LeCroy  
[www.lecroy.com](http://www.lecroy.com)

Local sales offices are located throughout the world.  
Visit our website to find the most convenient location.

© 2010 by LeCroy Corporation. All rights reserved. Specifications, prices, availability, and delivery subject to change without notice. Product or brand names are trademarks or requested trademarks of their respective holders.

WRXi-ADS-14Apr10  
PDF